

OBSAH BALENÍ



Art. 45178



Art. 452101


SPECIFIKACE

Počet módů:	5, 3 režimy svícení + 2 režimy blikání
Světelný tok v lumenech:	*700 LM
Výdrž baterie:	*1,5 – 6 h dle zvoleného režimu
Doba nabíjení:	*3 h
Typ baterie:	vyměnitelná 18500 Li-ion 1400mAh
Počet nabíjecích cyklů:	*400
Typ diody:	1x CREE XP-G3 LED 700 LM
Hmotnost světla:	120 g
IP stupeň ochrany:	IP65
Provozní teplota:	-10 °C + 40 °C
Materiál:	hliník
Velikost:	délka: 96 mm, průměr: 27 mm
Nabíjení:	USB-C kabelem včetně indikace


*Maximální naměřené hodnoty za ideálních podmínek testu.

MONTÁŽ

1. Nejprve nasadíte držák světla na řídítka.



2. Vložte světlo do držáku



VÝMĚNA BATERIE



UPOZORNĚNÍ

Vyvarujte se přímého pohledu do zapnutého světla. Abyste zabránili nežádoucímu osvětlení ostatních chodců a cyklistů vždy směřujte úhel světla směrem dolů. Vždy sejměte světlo při čištění a skladování kola ve venkovních prostorách (chráňte před deštěm a sněhem). Světlo vždy vypněte, pokud ho nepoužíváte. Světlo používejte na dobře větraném místě v exteriéru, hrozí riziko přehřátí. Zabudovaný tepelný senzor sníží výkon světla při přehřátí. Světlo je možné opět použít při běžné provozní teplotě. Světlo může rušit funkci ostatních elektronických přístrojů (např. cyklistické tachometry). Kapacita baterie se může snížit na cca 70-80 % po 300-400 nabíjecích cyklech. Kapacita baterie se snižuje při nižší okolní teplotě. Nevystavujte světlo ani baterii vysoké teplotě +40 °C (např. na horkém místě v autě), dlouhodobě nízkým teplotám pod 0 °C, vysoké vlhkosti a přímému slunečnímu záření. Skladujte na chladném, suchém místě mimo dosah dětí, zdrojů tepla a hořlavých materiálů. Chraňte před ohněm a vznětlivými látkami. Neponořujte světlo pod vodu. Světlo je voděodolné, lze ho tedy používat za mírného deště. Při silném dešti doporučujeme světlo uschovat na suchém místě. Neomývejte vodou a nepoužívejte agresivní čističe. Nerozebírejte ani jinak neupravujte světlo, baterii a příslušenství. Po uplynutí životnosti zlikvidujte světlo a baterii ekologicky dle platné vyhlášky. Nabíjení více než 5V může zničit baterii.

ZÁRUKA

Záruka nemůže být uplatněna na poškození způsobené vystavením nadměrným teplotám, mechanickým poškozením, neodborným servisním zásahem, úpravami, neodbornou montáží nebo nesprávným použitím.

Specifikace a provedení mohou být změněny bez předchozího upozornění. Aktuální verzi manuálu naleznete na stránkách www.FORCE.bike.

Prohlášení o shodě je dostupné na Force.bike.



NABÍJENÍ BATERIE


Pozor: Pokud baterii delší dobu nepoužíváte, nezapomeňte ji každé 3 měsíce plně nabít. Baterii skladujte na chladném a suchém místě. Po každém dlouhodobém používání ji znovu nabijte.

Indikátor napájení během nabíjení:

Nabíjení - bliká modře jeden po druhém
 Plně nabit - všechny 3 indikátory svítí trvale modře
 Slabý výkon - poslední indikátor bliká modře.

Indikátor napájení během používání:

Všechny 3 indikátory svítí - Výkon > 70%
 2 indikátory svítí - 30% < Výkon < 70%
 1 indikátor svítí - 10% < Výkon < 30%
 1 indikátor bliká - Výkon < 10%
 (Světlo se automaticky přepne do nouzového režimu)



NOUZOVÝ REŽIM


Jakmile se baterie téměř vybit, světlo se automaticky přepne do nouzového režimu 30 lumenů a vydrží svítit dalších 30 minut.

OVLÁDÁNÍ SVĚTLA



Stiskněte a podržte vypínač na 1 sekundu pro zapnutí/vypnutí.

Stiskněte vypínač pro změnu světelného režimu.



NABÍJENÍ BATERIE

Světlo nabíjejte pouze přiloženým USB kabelem / nabíječkou, jiný kabel/ nabíječka může způsobit poškození světla. Kabel / nabíječku po nabíjení vždy odpojte od světla a elektrické sítě, skladujte a používejte na suchém místě v interiéru. Nenechávejte při nabíjení bez dozoru. Po nabíjení vždy zajistíte USB vstup světla krytkou. Baterie se při nabíjení může zahřívat. K prodloužení životnosti doporučujeme častější nabíjení na menší kapacitu než 1 plné nabití. Vyhněte se ultra-rychlému nabíjení s vysokou kapacitou. Před dlouhodobým skladováním akumulátor nabíjte (baterie se musí nejméně 1 x za 6 měsíců dobít). Nenabíjejte, ani jinak nepoužívejte poškozené světlo.

PACKAGE CONTENTS



Art. 45178



Art. 452101

SPECIFICATION

Number of light modes:	5, 3 light modes + 2 flashing modes
Light intensity in lumens:	*700LM
Battery life:	*1,5 – 6 h
Charging time:	*3 h
Battery type:	vyměnitelná 18500 Li-ion 1400mAh
Number of charging cycles:	*400
Beam type:	1x CREE XP-G3 LED 700 LM
Light weight:	120 g
IP protection level:	IP65
Operating temperature:	-10 °C/ + 40 °C
Material:	alloy
Size:	length: 96mm, diameter: 27mm
Charging:	by USB-C cable with indication

*Maximum measured value under ideal test conditions

CHARGE BATTERY

Attention: If you do not use the battery for a long time, be sure to fully recharge it every 3 months. Please store the battery in a cool and dry place. Recharge battery after each 10n usage.

Power indicator during charging:

Charging - Flash in blue one by one

Fully charged - All 3 indicators on steady blue

Low power - The last indicator flash in blue

Power indicator during use:


All 3 indicators on - Power > 70%

2 indicators on - 30% < Power < 70%

1 indicators on - 10% < Power < 30%

1 indicators flash - Power < 10%


(Light will turn to Safe Mode automatically)




HOW TO MOUNT AND DISMOUNT

1. Install the bike bracket onto your bike's handle bar.

2. Install the light unit to the bike bracket



Wrap the rubber ring around your handlebar



Push the light into the bracket

SAFE MODE


When the battery is low, the light will turn to 30 lumens safe mode automatically and last for another 30 mins.

OPERATE THE LIGHT


 **CLICK**

Press the switch to change the light modes.

Press & hold switch for 1 second to switch on/off.



REPLACEABLE LI-ION BATTERY



18500 Li-ion battery

BATTERY CHARGING

Charge the light only with the supplied USB cable / charger, another cable / charger can cause light damage. Always unplug the cable / charger after charging, store and use in a dry place indoors. Do not leave unattended when charging. Always ensure the USB port of the light by the lid after charging. The battery may get warm when charging. Several part cycles are better for the battery than 1 full cycle. Avoid ultra-fast high capacity charging. Charge the battery before long term storage (the battery must be recharged at least once every 6 months). Do not charge or otherwise use the damaged light.

NOTICE

Do not look directly into the light. To prevent from blinding oncoming riders and walkers always adjust the light angle downwards. Always dismount the light while cleaning the bicycle and storage outside (protect from rain and snow). Switch the light off if not used. Use the light in well ventilated place outdoors – risk of overheating. Integrated overheat protection sensor will automatically decrease the light output in case of overheat. The light can be used again at standard operating temperatures. Light and battery can cause interference of other electrical devices (computers). Battery capacity can be reduced to approximately 70-80 % after 300-400 charging cycles. Battery capacity decreases at lower temperature. Do not expose the light or the battery to a high temperature of + 40 °C (hot place in the car), low temperatures below 0 °C, high humidity and direct sunlight. Store in a cool, dry place, keep away from children, heat source and inflammable material. Protect from fire and inflammable substances. Do not submerge in water. Light is water-resistant, it can be used in light rain. During heavy rain, it's recommended to store on dry place. Do not clean with water or aggressive cleaners. Do not disassemble or otherwise modify the light, battery and accessories. Dispose the light and battery ecologically according to valid regulations. Do not charge over 5V.

WARRANTY

The warranty cannot be applied to damage caused by exposure to excessive heat, mechanical damage, improper servicing, modifications, improper installation or improper use. Specifications and designs may be changed without prior notice. The current version of the manual can be found on the supplier's website www.FORCE.bike.



FORCE.BIKE

Dovozce/Výrobce, Importer/Producer
KCK Cyklosport-Mode s.r.o., Bartošova 348, 765 02 Otrokovice-Kvitkovice, CZ
www.kckcyklosport.cz, www.force.bike
Země původu Čína / Made in China